

## Technical Data Sheet

Technical Information		
Standby Power (ESP)	kVA	275
	kW	220
Prime Power (PRP)	kVA	250
	kW	200
Power Factor	cos $\phi$	0,8
Frequency	Hz	50
Voltage	V	230/400

### Standby Power (ESP)

Standby power is defined as the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 500 hours of operation per year under average of 70% load. Overloading is not permissible.

### Prime Power (PRP)

Prime power is defined as being the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hours.



### Weight and Dimensions

Length	mm	4000
Width	mm	1300
Height	mm	1900
Weight	kg	2800
Fuel tank capacity	Liters	350
Model	Soundproof canopy	
Noise level (at 7m)	dB	72

<b>Engine</b>		<b>Perkins - UK</b>
Model	-	1506A E88TAG3
No. of cylinders	-	6 in line
Engine Capacity	c.c.	8800
Bore	mm	112
Stroke	mm	149
Compression ratio	-	16,1:1
Cooling system	-	Water
Speed	rpm	1500
Engine Gross Power	kWm	258
Lubrication Oil Capacity	liters	41
Coolant Capacity	liters	29,6
Water jacket heater	-	Yes
Battery charger	-	Yes
Fuel Consumption	100%	55,5 L/h
	75%	41,6 L/h
	50%	28,9 L/h

<b>Alternator</b>		<b>Marelli - Italy</b>
Model	-	MJB250LB4
Power (Standby)	kVA	275
Excitation System	-	AVR, Brushless
Degree of Protection	-	IP 23

<b>Control panel</b>		<b>Deep Sea - UK</b>
<b>Instruments</b>	<b>Alarms</b>	
Voltmeter	Start-up failure	
Ammeter	Battery charge failure	
Frequency meter	Low oil pressure	
Hour meter	High engine water temperature	
Events history	Low Fuel Level	
Display LCD+LED	Emergency Stop	
Communication port RS 232 + RS 485	Over speed	

- Product certified according ISO 9001, ISO 14001 and CE standards.
- The information and images contained in this document are for general purposes and are subject to change without prior notice.



**MARRO ELECTRIC SYSTEMS**

Bucharest, Romania

office@marro.ro

**www.marro.ro**