

Technical Data Sheet

Technical Information		
Standby Power (ESP)	kVA	200
	kW	160
Prime Power (PRP)	kVA	180
	kW	144
Power Factor	cos ϕ	0,8
Frequency	Hz	50
Voltage	V	230/400

Standby Power (ESP)

Standby power is defined as the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 500 hours of operation per year under average of 70% load. Overloading is not permissible.

Prime Power (PRP)

Prime power is defined as being the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load. Average load should be 70%. The generator can be overloaded 10% for 1 hour per 12 hours.



Weight and Dimensions

Length	mm	3500
Width	mm	1200
Height	mm	1900
Weight	kg	2300
Fuel tank capacity	Liters	300
Model		Soundproof canopy
Noise level (at 7m)	dB	71

Engine		Perkins - UK
Model	-	1106A 70TAG3
No. of cylinders	-	6 in line
Engine Capacity	c.c.	7000
Bore	mm	105
Stroke	mm	135
Compression ratio	-	16:1
Cooling system	-	Water
Speed	rpm	1500
Engine Gross Power	kWm	177
Lubrication Oil Capacity	liters	16,5
Coolant Capacity	liters	21
Water jacket heater	-	Yes
Battery charger	-	Yes
Fuel Consumption	100%	41,2 L/h
	75%	30,9 L/h
	50%	20,6 L/h

Alternator		Marelli - Italy
Model	-	MJB250MB4
Power (Standby)	kVA	205
Excitation System	-	AVR, Brushless
Degree of Protection	-	IP 23

Control panel		Deep Sea - UK
Instruments	Alarms	
Voltmeter	Start-up failure	
Ammeter	Battery charge failure	
Frequency meter	Low oil pressure	
Hour meter	High engine water temperature	
Events history	Low Fuel Level	
Display LCD+LED	Emergency Stop	
Communication port RS 232 + RS 485	Over speed	

- Product certified according ISO 9001, ISO 14001 and CE standards.
- The information and images contained in this document are for general purposes and are subject to change without prior notice.



MARRO ELECTRIC SYSTEMS

Bucharest, Romania

office@marro.ro

www.marro.ro